

Hunter®

SRR Remote Control

SRR

An Easy to Use
Remote Control
for an Easy to
Handle Price



How does Hunter make their Simple and Reliable Series even simpler? By introducing the new SRR remote. Now there's no need to walk back to the controller to start or stop a watering cycle when doing new installation or maintenance. No need to have two workers winterize an irrigation system instead of just one. No need to get into the garage when a customer isn't

home. The SRR makes it possible for contractor and homeowner alike to operate a system without having to walk to (and tinker around with) the controller. Best of all, the SRR offers features that other remotes can't — including sturdy ABS construction, large LCD display and 4-button operation, internal antenna, 8 different run-time settings and variable station settings — at a price that can't be beat.



Homeowners:
*Simple and
Reliable Just
Got Simpler*

Ideally, you want the job of keeping your landscape green to be as easy as it can be. Well, Hunter's SRR remote has been created to do precisely that. With this handy new tool, you'll be able to activate zones with your SRC controller from anywhere in your yard. Ask your contractor for all the details on this valuable upgrade.



Easy indoor or outdoor installation



A) Typical indoor installation of SRR receiver unit.

B & C) Outdoor mounting of the SRR Smart Port™ allows instant access to the controller and eliminates the need to enter the building. Port can be mounted up to 50 feet from controller.

FEATURES & BENEFITS



- **Remote operation of any station or program**
Signal transmits up to 450 feet away
- **Compatible with Hunter products**
Designed to work with SRC, ICC and future controllers
- **128 different programmable security codes**
Allows multiple SRR systems to be used in the same area
- **Operates on one 9V battery for up to a year**
Automatic shutoff extends battery life when not in use
- **Variable remote activated station run times**
Adjusts programming to suit your changing needs
- **Weather-resistant Smart Port™ connection**
Allows temporary outdoor connection of remote receiver

Models

- SRR-Kit - Transmitter, receiver, wiring harness and owners manual
- SRR-SCWH - Smart Port™ Shielded Cable Wiring Harness and instructions
- SRR-TR - Transmitter
- SRR-R - Receiver

Dimensions

- Transmitter**
- Height: 4 3/4"
 - Width: 2 1/2"
 - Depth: 1 1/4"
- Receiver**
- Height: 4 3/4"
 - Width: 2 1/2"
 - Depth: 1"

Operating Specifications

- Address range: 0 - 127
- Maximum stations supported: 48
- Run times: Eight settings from 1 to 30 minutes
- Range: Up to 450 feet

Electrical Specifications

- Transmitter: 9V alkaline battery
- Receiver: 24VAC, 0.010 Amps from controller through Smart Port™ connector
- Receiver Type: Superheterodyne
- System Operating Frequency: 315 MHz

PRODUCT EXPLANATION

EXAMPLE: **SRR - KIT**

MODEL	FEATURES
SRR	KIT = Transmitter, receiver, wiring harness and owners manual SCWH = Wiring harness, Shielded cable TR = Transmitter R = Receiver

Available from:

